



Centium T5

CENTIUM ICN2S28N35M

Philips Advance Centium ballasts for T5 lamps at 120-277V are now available with our industry leading N-can at 9.5" x 1.3" x 1.0" or T-can at 14.17" x 1.18" x 1.06", which provides fixture manufacturers increased versatility in their newer generation fixture designs. These ballasts are compatible with all major energy-saving T5 linear lamps and have a variety of other features which makes them ideal for a variety of applications. The ballasts' programmed start ignition provides extended lamp life in frequent switching applications such as those where occupancy sensors are being used. They also feature lamp End-Of-Life (EOL) protection circuitry which safely removes power from the lamp at the end of lamp life.

Product data

General Information Lamp Type F28T5 Number of Lamps 1/2 piece/unit Ballast Type Electronic Fluorescent Base Model ICN2S28N Suitable For Outdoor Use Yes Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.7 Ignition Time (Nom) 1.5 s Ballast Factor (Nom) 1.03 Power Factor (Nom) 0.98 Input Current (Max) 0.53 A		
Number of Lamps 1/2 piece/unit Ballast Type Electronic Fluorescent Base Model ICN2S28N Suitable For Outdoor Use Yes Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.5 s Ballast Factor (Nom) 1.03 Power Factor (Nom) 0.98	General Information	
Ballast Type Electronic Fluorescent Base Model ICN2S28N Suitable For Outdoor Use Yes Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.7 Ignition Time (Nom) 1.5 s Ballast Factor (Nom) 0.98	Lamp Type	F28T5
Base Model ICN2S28N Suitable For Outdoor Use Yes Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.7 Ignition Time (Nom) 1.5 s Ballast Factor (Nom) 0.98	Number of Lamps	1/2 piece/unit
Suitable For Outdoor Use Yes Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.7 Ignition Time (Nom) 1.5 s Ballast Factor (Nom) 1.03 Power Factor (Nom) 0.98	Ballast Type	Electronic Fluorescent
Automatic Restart Yes Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.7 Ignition Time (Nom) 1.5 s Ballast Factor (Nom) 1.03 Power Factor (Nom) 0.98	Base Model	ICN2S28N
Operating and Electrical Input Voltage 120 to 277 V Input Frequency 50 to 60 Hz Total Harmonic Distortion USA 10 % Ignition Method Programmed Start Crestfactor (Nom) 1.7 Ignition Time (Nom) 1.5 s Ballast Factor (Nom) 1.03 Power Factor (Nom) 0.98	Suitable For Outdoor Use	Yes
Input Voltage	Automatic Restart	Yes
Input Voltage		
Input Frequency	Operating and Electrical	
Total Harmonic Distortion USA Ignition Method Programmed Start Crestfactor (Nom) 1.7 Ignition Time (Nom) 1.5 s Ballast Factor (Nom) 1.03 Power Factor (Nom) 0.98	Input Voltage	120 to 277 V
Ignition Method	Input Frequency	50 to 60 Hz
Crestfactor (Nom) 1.7 Ignition Time (Nom) 1.5 s Ballast Factor (Nom) 1.03 Power Factor (Nom) 0.98	Total Harmonic Distortion USA	10 %
Ignition Time (Nom) 1.5 s Ballast Factor (Nom) 1.03 Power Factor (Nom) 0.98	Ignition Method	Programmed Start
Ballast Factor (Nom) 1.03 Power Factor (Nom) 0.98	Crestfactor (Nom)	1.7
Power Factor (Nom) 0.98	Ignition Time (Nom)	1.5 s
	Ballast Factor (Nom)	1.03
Input Current (Max) 0.53 A	Power Factor (Nom)	0.98
	Input Current (Max)	0.53 A

Input Current (Min)	0.23 A
Input Power (Nom)	63-62 W
Rated Lamp Power	28 W
Wiring	
Color Input Terminals	No terminals
Color Output Terminals	No terminals
Wire Striplength	0.50/0.375 mm
Lamp Connection	Series
Wire Length by Color	See data sheet
Wire Gauge (Nom)	18AWG mm
Wire Type	Solid
Remote Wiring Configuration Allowed	Yes
Tandem Wiring Configuration Allowed	Yes
Through Wiring Configuration Allowed	Yes
Max Ballast-Lamp Distance Remote Wiring	20'
Max Ballast-Lamp Distance Tandem Wiring	Blue = 10'
Max Ballast-Lamp Distance Through Wiring	Blue = 10'


Datasheet, 2017, November 6 data subject to change

Centium T5

Connector Type	No connector
Tomporaturo	
Temperature	
T-Case Maximum (Nom)	70 °C
Mechanical and Housing	
Housing Material	Metal
Housing	N
Housing Dimensions	9.5" x 1.3" x 1.0"
Approval and Application	
EMC Immunity Standard	FCC Non-Consumer
Approval Marks	CSA certificate UL certificate CEC Listing FIDE
	Certificate NOM certificate RoHS Compliant

Hum And Noise Level	A				
UL Recognized	No				
Product Data					
Order product name	CENTIUM ICN2S28N35M				
EAN/UPC - Product	781087080733				
Order code	913710891602				
Numerator - Quantity Per Pack	1				
Numerator - Packs per outer box	30				
Material Nr. (12NC)	913710891602				
Net Weight (Piece)	373.000 g				

Dimensional drawing



ELE BALLAST (2) F28T5 120-277V

Product	A1	A2	B1	C1
CENTIUM ICN2S28N35M	9.50 in	8.90 in	1.30 in	1.00 in

