



Core & Coil (71A) MH 175W - 450W

CORE & COIL HID MH BAL 350W M131 QUAD KIT

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

Product data

| General Information | | |
|------------------------------------|------------------------|--|
| ANSI Code | M131-M171 | |
| Lamp Type | 350W MH | |
| Number of Lamps | 1 piece/unit | |
| Circuit Type | SUPER-CWA | |
| Ballast Type | Magnetic HID | |
| Base Model | 71A5993A | |
| Core Size | 4 1/4 x 4 3/4 (2 coil) | |
| Suitable For Outdoor Use | Yes | |
| Ignitor Catalog Number | LI533-H4 | |
| Ignitor Temperature Rating | 105°C | |
| Capacitor Value | 22.5 MFD | |
| Capacitor Catalog Number | 7C225P40 | |
| Capacitor Requirements | 345V | |
| Capacitor Temperature Rating | 105°C | |
| Capacitor Diameter/Oval Dimensions | 1.75 in | |
| Capacitor Height | 4.8 in | |
| Automatic Restart | No | |


| Operating and Electrical | |
|---------------------------------|---|
| Input Voltage | 120/208/240/277 V |
| Input Frequency | 60 Hz |
| Power (Rated) (Nom) | 350 W |
| Inp. Current (Open Circuit) | 2.2/1.3/1.1/1 A |
| Input Current (Starting) | 2.2/1.3/1.1/1 A |
| Input Current (Short Circuit) | 1.75-2.65/1.0-1.55/0.9-1.35/0.75-1.15 A |
| Secondary Short Circuit Current | 3.25-4 A |
| Constant Wattage Deviation | 10% |
| Ballast Factor (Nom) | 1 |
| Power Factor (Nom) | 0.90 |
| Nominal Open Circuit Voltage | 270 V |
| Input Current (Operating) (Nom) | 3.4/2/1.7/1.5 A A |
| Input Power (Nom) | 400 W |
| Rated Lamp Watts | 350W W |
| Wiring | |
| Wire Striplength | 0.5 mm |
| Wire Length By Color | 12" |
| Wire Type | Stranded |

Core & Coil (71A) MH 175W - 450W


| Remote Wiring Configuration Allowed | Yes |
|---|------------------------------------|
| Max Ballast-Lamp Distance Remote Wiring | 2' |
| Recommended Fuse Value | 10/7/5/5 A |
| | |
| Approval and Application | |
| Open Circuit Voltage Test (Volts) | 240-300 V |
| Approbation Marks | ULR CSA certificate RoHS Compliant |
| Temperature Marking | D/C/C/C |
| UL Recognized | Yes |
| Hipot Test (1 Minute) | 2000 V |
| Hipot Test (2 Seconds) | 2500 V |
| UL Insulation Class | H(180°C) |
| | |

| UL Temperature Code | 1029D |
|---------------------------------|-----------------------------|
| | |
| Product Data | |
| Order product name | CORE & COIL HID 71A5993001D |
| EAN/UPC - Product | 781087097502 |
| Order code | 71A5993001D |
| Numerator - Quantity Per Pack | 1 |
| Numerator - Packs per outer box | 1 |
| Material Nr. (12NC) | 913700535509 |
| Net Weight (Piece) | 5.194 kg |

Dimensional drawing



MH BAL 350W M131 QUAD KIT





© 2015 Philips Lighting Holding B.V. All rights reserved. Philips Lighting reserves the right to make changes in specifications and/or to discontinue any product at any timewithout notice or obligation and will not be liable for any consequences resulting from the use of this publication.

www.lighting.philips.com 2015, November 29 - data subject to change