


Meter Centers



Surface Mount, Side-by-Side Meter-Load Center Combination, 1-Phase, 3-Wire 120/240V AC


- UL listed
- 22,000 AIC Rated
- Pad locking provisions on all devices
- Side hinge doors removable by backing out only one screw
- Suitable for use only as service entrance equipment
- Contact local utility to confirm meter socket approval prior to installation
- See end of section for dimensions and wiring diagrams

**MC0816B1200TH (shown)
MC0816B1XXX(R)TH**



200A OH/UG feed, 8 circuit, with feed thru lugs.

**MC0816B1400RLTM
MC0816B1350RLTM**



One factory installed main, provisions for up to 200A field installed main, 8 circuits, lever bypass.

MC3042B1400SDL



400A meter load center combination, 30 space/40 circuit lever bypass

MC2442B1400SDB



400A bolt in K4 socket with 400A main

Catalog Number	Amp Rating (Cont.)	Utility Incoming	Bypass Type	No. of Spaces	No. of Circuits	Dimensions (inches)			Main Breaker	Short Circuit Rating	Hub Provision	5th Jaw	Cover Type
						H	W	D					

Meter-Load Center Combination, 150-200amp, Full Loadcenter Width

MC0816B1150TH ^①	150	OH/UG	None	8	16	21.0	22.9	5.0	QN2150RH	22,000	2-RX	EMC5J	Ring
MC0816B1200TH ^①	200								QN2200RH				Ringless
MC0816B1150RTH ^①	150								QN2150RH				Ringless
MC0816B1200RTH ^①	200								QN2200RH				Ringless
MC1224B1125	125	OH/UG	None	12	24	16.0	22.89	5.0	Q2125H	22,000	RX	EMC5J	Ring
MC1224B1125R	125					32.0	14.0	5.0	EQ9575/ EQ9677		RX-top HC-bot	EC5J2	Ringless
MC2040B1150	150	OH/UG	None	20	40	18.0	22.9	5.0	QN2150RH	22,000	RX	EMC5J	Ring
MC2040B1200	200								QN2200RH				Ringless
MC2040B1150R	150								QN2150RH				Ringless
MC2040B1200R	200								QN2200RH				Ringless

Meter-Load Center Combination, 350-400amp, Lever Bypass

MC0408B1400RLTM ^①	320	OH/UG	HQ Lever	4	8	29.0	27.0	6.0	QN2200H	22,000	HD	H35815-2	Ringless
MC0816B1350RLTM ^①				8	16				QN2150H				
MC0816B1400RLTM ^①				8	16				QN2200H				

Meter-Load Center Combination, 400amp, Lever Bypass, Underground Feed Only

MC0816B1400SDL	320	UG	HQ Lever	8	16	39.7	30.2	6.4	(1) QN & Provisions for (1)QN or (1)QP	22,000	HD	H35815-2	Ringless
MC2442B1400SDL				24	42	39.5	30.3	6.0	JXD6				
MC3042B1400SDL				30	42	39.7	30.2	6.4	(1) QN & Provisions for (1)QN or (1)QP				

Meter-Load Center Combination, 400amp, K4 Bolt-In Meter Socket, Underground Feed Only

MC2442B1400SDB	400 ^②	UG	Bolt In K4 No By- pass	24	42	39.7	30.2	6.4	Factory JXD6	22,000	HD	—	Ringless
MC3042B1400SDB				30	42				Factory QN2200RH Field QP(H), QNR(H)			—	

① Feed thru lugs included.

② Bolt-in meter socket. This device should not be confused with class 320amp lever bypass devices. Device can not be converted to lever bypass. Installer should ensure device approval prior to installation.