


Circuit Breaker Enclosures & Small Load Centers



- Ideal for Narrow stud applications
- Eliminated "notching" needed for standard Load Centers
- Outdoor Load Center with factory installed Ground Fault Breaker
- Two extra circuits
- Factory installed feed-through lugs
- Main Breaker or Main Lug panels available



Spa Panels

Ampere Rating	No. of Spaces	Max. Circuits	Catalog Number	Dimensions ^③		
				Height	Width	Depth
125	2	4	LW004NRSPA50 [®]	12¼	6⅝	4¼
125	2	4	LW004NRSPA60 [®]	12¼	6⅝	4¼

Renovation Panels - 3 Wire 120/240V AC

200	24	40	LC024PFR	30	14	3⅝
100	10	20	LC110DFCGP [®]	14¾	12⅝	3⅝

Outdoor^① Trailer Panels - 120/240V AC 208Y/120V AC

Amps Max	No. of Spaces	Max. Circuits	Indoor Type 1 Catalog No.	Dimensions ^③			Main Breaker	
				Height	Width	Depth		
100	2	4	LW102NL ^①	12½	6	4¼	MP2100	Factory
200	4	8	LW204TL ^①	20	11⅝	4¼	MPD2200R	Factory
200	4	8	LW004TR [®]	20	11⅝	4¼	MD-T(R), MD-HT(R)	Field
200	8	16	LW0816L1200TR [®]	29	14¼	4½	MBK150M or MBK200M	Field

2-8 Circuit, 60-125 Amperes (no door)

Amps Max.	No. of Spaces	Max. Circuit	Indoor Type 1 Catalog Number ^②	Dimensions ^③			Outdoor Type 3R ^① Catalog Number	Dimensions ^③		
				Height	Width	Depth		Height	Width	Depth
60	2	4	LC002GS	9⅞	5⅝	2⅝	LW002GR [®]	8¼	5⅝	4½
100	3	3	LP003CS	17⅞	7½	5⅝	—	—	—	—
125	2	4	LC002HS	17⅞	7⅞	4¼	LW002HR	8¼	5⅝	4½
125	4	8	LC004NF	12⅞	6⅞	3½	—	—	—	—
125	4	8	LC004NS	12⅞	6⅞	3½	LW004NR	12¼	6⅞	4¼
200	2	4	LC004VS	19¼	8½	4	LW004VR	19⅞	8⅞	4⅞
225	2	4	—	—	—	—	LW002QR	27	10⅞	5⅞

8-16 Circuit, 125 Amperes (with door)

125	8	16	LC008DF	14¼	12⅞	3⅞	—	—	—	—
125	8	16	LC008DS	14¼	12⅞	3⅞	LW008NR	14¼	12⅞	4⅞
125	8	16	LC008DFG	14¼	12⅞	3⅞	—	—	—	—
125	8	16	LC008DSG	14¼	12⅞	3⅞	—	—	—	—

Enclosed Breakers

100	2	4	LC100CS	17⅞	7⅞	4¼	LW100CR	17⅞	7⅞	4⅞
200	2	4	LC200VS	19¼	8½	4	LW200VR	19⅞	8⅞	4⅞
225	3	3	—	—	—	—	LW903QR	27	10⅞	5⅞

① Hub provision only. Closure plate included. Panels through 225A require HS type hub.

② Cover type is specified by character in 7th (usually last) position, as follows:

- S = Surface
- F = Flush
- C = Combination Surface/Flush

③ Dimensions shown are representative of outside box length, width & depth (±¼") and do not include allowance for mounting bumps, endwalls, hubs or hardware protrusions. Allow approximately 1¼" additional in length and width dimensions for surface or combination overhang. Consult factory for specific details if required.

④ Use of 60A GFCI requires use of 75°C copper wire.

⑤ Use neutral lug kit ECLK1 or ECLK2 as required.

⑥ Panel includes factory-installed ground bar.

⑦ Maximum breaker 100A.

⑧ Uses HA type hub. Closure plate included.

For KO diagram, see Section 1 KO diagram for W0204ML1060

⑨ Accepts type MQ breakers.

⑩ For service entrance use only 200A max. main breaker. Main breaker must be field added.

⑪ LW102NL shipped with ECHS125 hub instead of closure plate. LW204TL shipped with ECHS200 hub instead of closure plate.

⑫ Two MP115 and one MP230 provided.

⑬ 50 Amp, 2-pole GFCI breaker installed.

⑭ 60 Amp, 2-pole GFCI breaker installed.

⑮ Uses ECHA hub type.