



PE10000 Series Pool/Spa Control System with Type 3R Power Center

- Includes P1353ME 3-circuit mechanism and power center
- P1353ME controls single and two-speed filter pumps, cleaner/booster pumps, and pool/spa landscape lighting

	Model #	Mechanism	Accessory	Switch
A.	PE10000	Power Center only	—	—
	PE15300	P1353ME	—	3-SPST
B.	PE15300F	P1353ME	Freeze Probe	3-SPST

Ratings:

P1353ME Switch Ratings Each Circuit (SPST):
Input Voltage: 120/240, VAC 50/60 Hz.

Contacts:
 17 A Resistive 120/240 VAC,
 5 A Tungsten 120/240 VAC,
 17 FLA, 80 LRA 120/240 VAC
Auxiliary Switch: 2 A, 24 VAC

Power Center Dimensions: 16 1/2" (41.9 cm) H x
 10 3/8" (27.6 cm) W x 4 1/4" (10.8 cm) D

Knockouts:

Bottom: (1) 1.09" \emptyset through hole,
 (3) 1/2", (7) 1/2" - 3/4", (2) 3/4" - 1"

Left: Two 1/2" - 3/4"

Back: (1) 1/2" - 3/4", (1) 3/4" - 1"

Right: (1) 1 3/4" x 2 3/4"

Warranty: 1 year

PE20000 Series 60 Amp Pool/Spa Control System with Type 3R Load Center

- 60 Amp 4-position breaker base
- Includes P1353ME 3-circuit mechanism and load center
- P1353ME controls single and two-speed filter pumps, cleaner/booster pumps, and pool/spa landscape lighting

	Model #	Mechanism	Accessory	Switch
C.	PE20000	Load Center only	—	—
	PE25300	P1353ME	—	3-SPST
D.	PE25300F	P1353ME	Freeze Probe	3-SPST

Ratings:

P1353ME Switch Ratings For Each Circuit (SPST):
Input Voltage: 120/240 VAC, 50/60 Hz.

Contacts:
 17 A Resistive 120/240 VAC,
 5 A Tungsten 120/240 VAC,
 17 FLA, 80 LRA 120/240 VAC
Auxiliary Switch: 2 A, 24 VAC

Load Center Dimensions: 14 3/4" (37.5 cm) H x
 14 3/4" (37.5 cm) W x 4 1/4" (10.8 cm) D

Knockouts:

Bottom: (1) 1.09" \emptyset through hole,
 (6) 1/2" - 3/4", (3) 3/4" - 1"

Left: (2) 1/2" - 3/4"

Back: (1) 3/4" - 1"

Right: (1) 1 3/4" x 2 3/4" for mounting
 switches or GFCI

Warranty: 1 year

For further information on P1353ME mechanism, see page 120.

Wiring devices may be installed in the power and load centers
 (order (4) 21T156A standoffs for mounting). See page 154.

For accessories, see page 153.