










 <p>5-20R2GFCI</p>	 <p>5-20R2</p>	 <p>(2) 5-20R2GFCI</p>	 <p>(2) 5-20R2GFCI</p>	 <p>(2) 5-20R2</p>	 <p>(2) 5-20R2</p>
A U010C010	B U010G	C U011C010	D U011CTL010	E U011G	F U011GTL

 <p>R32U (2) 5-20R2GFCI</p>	 <p>R32U 5-20R2</p>	 <p>BR32U 5-20R2</p>	 <p>R32U 5-20R2GFCI</p>	 <p>BR32U 5-20R2GFCI</p>	 <p>R32U 5-20R2</p>
G U031C010	H U040G	I U040GTL	J U041C010	K U041CTL010	L U041G

RV Products

FIG.	UL	LUG TYPE	MODEL NUMBER	RECEPTACLES	CIRCUIT PROTECTION	AMP	VOLTS	WIRE RANGE*	CABINET SIZE	HUB OPENING	LOAD & NEUTRAL BAR	UNIT WT.	STD. PKG.
A	Y	STANDARD	U010C010	5 20R2GFC	CB120	20	120	B	6 X 9	Y		7	4
B	Y	STANDARD	U010G	5 20R2	GF 120	20	120	B	6 X 9	Y		7	4
C	Y	STANDARD	U011C010	(2) 5 20R2GFC	(2) CB120 SPACE CB120	70	120/240	P	6 X 14	Y	LC33N7	10	4
D	Y	LOOP FEED	U011CTL010	(2) 5 20R2GFC	(2) CB120 SPACE CB120	100	120/140	W	9 X 17	Y	LC33N1T	14	1
E	Y	STANDARD	U011G	(2) 5 20R2	(2) GF 120 SPACE CB120	70	120/240	P	6 X 14	Y	LC33N7	10	4
F	Y	LOOP FEED	U011GTL	(2) 5 20R2	(2) GF 120 SPACE CB120	100	120/240	W	9 X 17	Y	LC33N1T	14	1
G	Y	STANDARD	U031C010	R32U (2) 5 20R2GFC	CB130 (2) CB120 SPACE (2) CB120	100	120/240	AA	9 X 17	Y	LC55N1	16	1
H	Y	STANDARD	U040G	R32U 5 20R2	GF 130 GF 120 SPACE CB120	70	120/240	P	6 X 14	Y	LC33N7	10	4
I	Y	LOOP FEED	U040GTL	BR32U 5 20R2	GF 130 GF 120 SPACE CB120	100	120/240	W	9 X 17	Y	LC33N1T	14	1
J	Y	STANDARD	U041C010	R32U 5 20R2GFC	CB130 CB120 SPACE CB120	70	120/240	P	6 x 14	Y	LC33N7	10	4
K	Y	LOOP FEED	U041CTL010	BR32U 5 20R2GFC	CB130 CB120 SPACE CB120	100	120/240	W	9 x 17	Y	LC33N1T	14	1
L	Y	STANDARD	U041G	R32U 5 20R2	CB130 GF 120 SPACE CB120	70	120/240	P	6 x 14	Y	LC33N7	10	4

* Wire Range Table on page 92

MODEL NUMBER	REPLACEMENT PARTS		CABINET SIZE pages 90 91	ENCLOSURE STYLE page 90	CABINET DIMENSIONS **			KNOCKOUT FIGURE page 90
	METER SOCKET	POST LUGS			HEIGHT	WIDTH	DEPTH	
					A	B	C	
R041G	MSR100930		9 X 30	B	30"	9 3/4"	5 3/16"	2
R041GB6	B	LT100B350	9PT					
R041GP6	MSR100P9	LT100S250	9PT					
R055C010	MSR100930		9 X 30	B	30"	9 3/4"	5 3/16"	2
R055G	MSR100930		9 X 30	B	30"	9 3/4"	5 3/16"	2
R075C010	MSR100930		9 X 30	B	30"	9 3/4"	5 3/16"	2
R075CB6010	MSR100P9	LT100B350	9PT					
R075CP4010	MSR100P9	LT100S250	9PT					
R075CP6010	MSR100P9	LT100S300	9PT					
R075CP6031	MSR100P9	LT100S300	9PT					
R075GB6	B	LT100B350	9PT					
R075GP6	MSR100P9		9PT					
R076C010	MSR100930		9 X 30	B	30"	9 3/4"	5 3/16"	2
R355CP6010	MSR100P9		9PT					
R355CP6031	MSR100P9		9PT					
R355G	MSR100930		9 X 30	B	30"	9 3/4"	5 3/16"	2
R355GP6	MSR100P9		9PT					
U004CB4010		LT100B350	9PT					
U004CB6010		LT100B350	9PT					
U004CP4010		LT100S250	9PT					
U004CP4031		LT100S300	9PT					
U004CP6010		LT100S300	9PT					
U010C010			6 X 9	A	9 1/8"	7 1/4"	5 3/16"	1
U010G			6 X 9	A	9 1/8"	7 1/4"	5 3/16"	1
U011C010			6 X 14	A	14 3/8"	7 1/4"	5 3/16"	1
U011CP4010		LT100S300	6PT					
U011CP6010		LT100S300	6PT					
U011CTL010			9 X 17	A	17 3/8"	9 3/4"	5 3/16"	2
U011G			6 X 14	A	14 3/8"	7 1/4"	5 3/16"	1
U011GB4		LT100B250	6PT					
U011GB6		LT100B250	6PT					
U011GP4		LT100S250	6PT					
U011GP6		LT100S300	6PT					
U011GTL			9 X 17	A	17 3/8"	9 3/4"	5 3/16"	2
U031C010			9 X 17	A	17 3/8"	9 3/4"	5 3/16"	2
U040G			6 X 14	A	14 3/8"	7 1/4"	5 3/16"	1
U040GP4		LT100S250	6PT					
U040GP6		LT100S300	6PT					
U040GP6010		LT100S250	6PT					
U040GTL			9 X 17	A	17 3/8"	9 3/4"	5 3/16"	2
U041C010			6 X 14	A	14 3/8"	7 1/4"	5 3/16"	1
U041CB4010		LT100B250	6PT					
U041CB4L10		LT100B250	6PT					
U041CB6010			6PT					
U041CB6L10		LT100B250	6PT					
U041CP4010		LT100S250	6PT					
U041CP4031		LT100S250	6PT					
U041CP4039		LT100S350	6PT					
U041CP4L10		LT100S250	6PT					
U041CP6010		LT100S300	6PT					
U041CP6031		LT100S250	6PT					
U041CP6039		LT100S350	6PT					
U041CP6L10		LT100S300	6PT					
U041CTL010			9 X 17	A	17 3/8"	9 3/4"	5 3/16"	2
U041CTLL10			9 X 17	A	17 3/8"	9 3/4"	5 3/16"	2
U041G			6 X 14	A	14 3/8"	7 1/4"	5 3/16"	1
U041GB4		LT100B250	6PT					

B - Front (nline Side) MSR100P9 Back (Powerhead side) MSR100 P

** For Post Cabinet Sizes and Dimensions see page 91