

Product Code	Product #	Number of Lamps	Primary Lamp	Starting Type	Voltage	Power Factor	Ballast Factor
<b>Compact Fluorescent Kits</b>							
EP2CF13PS/MV/DC/K	52102	2	PL13D/E/G24q	PS	120 / 277	0.99	1.00
EP2CF18PS/MV/DC/K	52104	2	PL18D/E/G24q	PS	120 / 277	0.99	0.95
EP2CF26PS/MV/DC/K	52106	2	PL26D/E/G24q	PS	120 / 277	0.99	1.00
EP2CF42PS/MV/DC/K	52108	2	PL42T/E/GX24q	PS	120 / 277	0.99	1.00
EP2CF42RS/MV/DC/K	52110	2	PL42T/E/GX24q	RS	120 / 277	0.99	0.90
<b>Compact Fluorescent GU24 Adapter</b>							
EICF13RS/120/GU24	52200	1	PL13D/E/G24q	RS	120	0.54	1.02
EICF18RS/120/GU24	52201	1	PL18D/E/G24q	RS	120	0.55	0.86
EICF26RS/120/GU24	52202	1	PL26D/E/G24q	RS	120	0.57	0.80
<b>Linear Fluorescent</b>							
E108RS/120	50102	1	F4T5	RS	120	>0.5	1.00
E114RS/120	50104	1	F6T5	RS	120	>0.5	1.00
E120RS/120	50108	1	F20T12	RS	120	>0.5	0.90
E126RS/120	50106	1	F13T8	RS	120	>0.5	1.10
E139HO/RS/120	50138	1	F39T5/HO	RS	120	>0.5	0.88
E154HO/RS/120	50140	1	F54T5/HO	RS	120	>0.5	0.95
E220RS/120	50110	2	F20T12	RS	120	>0.5	0.88
E232IS/120/R/MC	50118	2	F32T8	IS	120	>0.5	0.81
E432IS/120/R/SL	50158	4	F32T8	IS	120	>0.5	0.80
EP132IS/MV/MC	50112	1	F32T8	IS	120 / 277	0.99	0.88
EP2110RS/120	50162	2	F96T12/HO	RS	120	0.99	0.90
EP2110RS/MV	50164	2	F96T12/HO	RS	120 / 277	0.99	0.90
EP228PS/MV	50166	2	F28T5	PS	120 / 277	0.99	1.03
EP232IS/120/MC	50176	2	F32T8	IS	120	0.99	0.88
EP232IS/120/SL	50114	2	F32T8	IS	120	0.99	0.88
EP232IS/H/MV/SL	50115	2	F32T8	IS	120 / 277	0.99	1.18
EP232IS/L/MV/HE	50119	2	F32T8	IS	120 / 277	0.99	0.77
EP232IS/MV/HE	50123	2	F32T8	IS	120 / 277	0.99	0.87
EP232IS/MV/MC	50116	2	F32T8	IS	120 / 277	0.99	0.88
EP239HO/PS/MV	50142	2	F39T5/HO	PS	120 / 277	0.98	1.00
EP240RS/120	50128	2	F40T12	RS	120	0.99	0.88
EP240RS/MV	50160	2	F40T12	RS	120 / 277	0.99	0.88
EP254HO/PS/MV	50144	2	F54T5/HO	PS	120 / 277	0.98	1.00
EP259IS/MV	50136	2	F96T8	IS	120 / 277	0.99	0.88
EP260IS/120	50132	2	F96T12/ES	IS	120	0.99	0.95
EP260IS/277	50134	2	F96T12/ES	IS	277	0.98	0.95
EP275IS/MV	50130	2	F96T12	IS	120 / 277	0.99	0.88
EP332IS/120/SL	50120	3	F32T8	IS	120	0.99	0.88
EP332IS/H/MV/SL	50121	3	F32T8	IS	120 / 277	0.99	1.18
EP332IS/L/MV/HE	50168	3	F32T8	IS	120 / 277	0.99	0.78
EP332IS/L/MV/SL	50154	3	F32T8	IS	120 / 277	0.99	0.77
EP332IS/MV/HE	50170	3	F32T8	IS	120 / 277	0.99	0.87
EP332IS/MV/MC	50122	3	F32T8	IS	120 / 277	0.99	0.88
EP432IS/120/SL	50124	4	F32T8	IS	120	0.99	0.88
EP432IS/L/MV/HE	50172	4	F32T8	IS	120 / 277	0.99	0.78
EP432IS/L/MV/SL	50156	4	F32T8	IS	120 / 277	0.99	0.77
EP432IS/MV/HE	50174	4	F32T8	IS	120 / 277	0.99	0.88
EP432IS/MV/MC	50126	4	F32T8	IS	120 / 277	0.99	0.88
<b>Circline</b>							
EICR22RS/120/PT	50150	1	FC8T9	RS	120	>0.5	0.90
EICR32RS/120/PT	50146	1	FC12T9	RS	120	>0.5	1.00
E2CR72RS/120/PT	50148	2	FC12T9+FC16T9	RS	120	>0.5	0.70
<b>Electronic Sign</b>							

Product Code	Product #	Number of Lamps	Primary Lamp	Starting Type	Voltage	Power Factor	Ballast Factor
ESB/0216/12	57114	1	T12/HO	IS	120 / 277	0.90	-
ESB/0432/14	57116	1	T12/HO	IS	120 / 277	0.90	-
ESB/1040/14	57118	1	T12/HO	IS	120 / 277	0.98/0.95	-
ESB/0848/46	57120	1	T12/HO	IS	120 / 277	0.98/0.97	-
<b>Electronic Metal Halide</b>							
⊗ C156/20E/MV/BE	55504	1	20W CDM	PS	120/277	0.96	1.00
⊗ C156/20E/MV/SE	55502	1	20W CDM	PS	120/277	0.96	1.00
⊗ C130/35E/MV/BE	55508	1	39W CDM	PS	120/277	0.96	1.00
⊗ C130/35E/MV/SE	55506	1	39W CDM	PS	120/277	0.96	1.00
⊗ C139/70E/MV/BE	55512	1	70W CDM	PS	120/277	0.98	1.00
⊗ C139/70E/MV/SE	55510	1	70W CDM	PS	120/277	0.96	1.00

⊗NEW ITEM!