



Powering Business Worldwide

pe.eaton.com

Stud-Mount Fuse

FWA-1000A

UPC:051712795463

Dimensions:

- **Height:** 1.5 IN
- **Length:** 3.5 IN
- **Width:** 1.75 IN

Weight:.42 LB

Warranties:

- Not Applicable

Specifications:

- **Type:** FWA, North American style stud-mount
- **Application:** DC common bus, DC drives, power converters/rectifiers, reduced voltage starters
- **Interrupt Rating:** 200 kAIC (70-400A), 200 kAIC (450-1000A), 20 kAIC @ 150 Vdc (70-800A), 100 kAIC @ 80 Vdc (70-1000A)
- **Fuse Indicator:** Non Indicating
- **Packaging Type:** Standard
- **Current Rating:** 1000A RMS
- **Pre Arc (I²T):** 170000
- **Clearing (I²T):** Clearing at 150V: 510000
- **Connection:** Blade end X blade end
- **Watt Losses:** 60W
- **Mounting:** Stud

Supporting documents: No Data

Certifications:

- UL Recognized

Product compliance:

- CE Marked



