PHILIPS Lighting



Core & Coil (71A) HPS ~LT~ 200W

CORE & COIL HID 71A8007500D

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

Product data

General Information		
ANSI Code	S54	
Lamp Type	100W HPS	
Number Of Lamps	1 piece/unit	
Circuit Type	R-HPF	
Ballast Type	Magnetic HID	
Base Model	71A8007	
Core Size	2 5/8 x 2 3/16	
Suitable For Outdoor Use	Yes	
Ignitor Catalog Number	LI551-H4	
Ignitor Temperature Rating	105°C	
Capacitor Value	36 MFD	
Capacitor Catalog Number	7C360M12RA	
Capacitor Requirements	120V	
Capacitor Temperature Rating	105°C	
Capacitor Diameter/Oval Dimensions	1.65 in	
Capacitor Height	2.75 in	
Automatic Restart	No	


Operating and Electrical	
Input Voltage	120 V
Input Frequency	60 Hz
Power (Rated) (Nom)	100 W
Input Current (Open Circuit)	1.8 A
Input Current (Starting)	1.5 A
Input Current (Short Circuit)	1.0-1.6 A
Secondary Short Circuit Current	2.4-3.6 A
Constant Wattage Deviation	Within Trapezoid
Ballast Factor (Nom)	1
Power Factor (Nom)	0.90
Open Circuit Voltage	120 V
Input Current (Nom)	1.05 A A
Input Power (Nom)	115 W
Rated Lamp Power	100W W
Wiring	
Wire Striplength	0.5 mm
Wire Length By Color	12"
Wire Type	Stranded

Core & Coil (71A) HPS ~LT~ 200W


Remote Wiring Configuration Allowed	Yes
Max Ballast-Lamp Distance Remote Wiring	2'
Recommended Fuse Value	5 A
Approval and Application	
Open Circuit Voltage Test (Volts)	114-126 V
Approval Marks	ULR CSA certificate RoHS Compliant
Temperature Marking	A
UL Recognized	Yes
Hipot Test (1 Minute)	2000 V
Hipot Test (2 Seconds)	2500 V
UL Insulation Class	H(180°C)

UL Temperature Code	1029A
Durder (Data	
Product Data	
Order product name	CORE & COIL HID 71A8007500D
EAN/UPC - Product	781087800751
Order code	913700526209
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	12
Material Nr. (12NC)	913700526209
Net Weight (Piece)	1.275 kg

Dimensional drawing



HPS BAL 100W S54 120V C&C





© 2016 Philips Lighting Holding B.V. All rights reserved. Philips Lighting reserves the right to make changes in specifications and/or to discontinue any product at any timewithout notice or obligation and will not be liable for any consequences resulting from the use of this publication.

www.lighting.philips.com 2016, February 1 - data subject to change