


# MC/AC Cable Support Bracket with Z Purlin Clip – MCS101AF14



- Neatly isolates, supports and secures MC/AC cables
- Properly spaces MC/AC cable to help eliminate bundling and NEC® & CEC derating issues
- Results in a "neat and workmanlike" installation



|                             |                   |
|-----------------------------|-------------------|
| Part Number                 | MCS101AF14        |
| Isolated Ground Cable Size  | 12-3 to 8-2       |
| MC/AC Cable Size            | 10-3 to 8-3       |
| Super Neutral Cable Size    | 12-3 to 10-2      |
| Material                    | Steel             |
| Finish                      | Electrogalvanized |
| Cable Capacity              | 7                 |
| Flange Thickness [FT]       | 1/16" – 1/4"      |
| Outer Diameter [OD]         | 0.56" – 0.69"     |
| Certifications              | cULus             |
| Standard Packaging Quantity | 25 pc             |
| UPC                         | 78285646977       |

NEC is a registered trademark of, and National Electrical Code [NEC] standard is a copyright of the National Fire Protection Association, Inc. UL, UR, cUL, cUR, cULus and cURus are registered certification marks of UL LLC.

#### WARNING

Pentair products shall be installed and used only as indicated in Pentair's product instruction sheets and training materials. Instruction sheets are available at [erico.pentair.com](http://erico.pentair.com) and from your Pentair customer service representative. Improper installation, misuse, misapplication or other failure to completely follow Pentair's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.

© 2017 Pentair. All rights reserved.

Pentair, CADDY, CADWELD, CRITEC, ERICO, ERIFLEX, ERITECH and LENTON are owned by Pentair or its global affiliates.

All other trademarks are the property of their respective owners. Pentair reserves the right to change specifications without prior notice.

