

LED Wall Sconce

Wall mounted • Damp location listed **PROGRESS LED**

Description:

Planck LED wall fixtures use indirect illumination to provide a dramatic architectural feature to any space. A brushed metal beam sports a sleek chrome accent to add visual interest to the minimalist form. Suitable for residential or commercial applications.

Specifications:

- Brushed Nickel (-009) (plated)
- Steel construction
-
- Rectangular design pairs with a geometric back plate to create Planck
- 1-light 16-watt LED wall bracket
- Brushed Nickel finish with linear chrome accents
- LED source provides indirect lighting as it reflects against a wall, offering both visual interest and functional illumination
- Measures 4 3/4" W x 16" H
- 37.5 lumens per watt
- Warm white 3000K lighting color, 600 lumens and 90+CRI
- Design accommodates Modern, Mid-Century and Luxe lighting applications within the bath and vanity area
- Damp location listed
- Dimmable to 10% brightness (See Dimming Notes)
- Backplate covers a standard 4" octagonal recessed outlet box
- Mounting plate for outlet box included
- 6" of wire supplied
- Complies with "Americans with Disabilities Act" - ADA

Performance:

Number of Modules	1
Input Power	16w
Input Voltage	120 V
Input Frequency	60 Hz
Lumens/LPW	600/37.5 (LM-79)
CCT	3000 K
CRI	90 CRI
Life (hours)	(L70/TM-21)
FCC	Meets FCC Title 47, Part 15 Class B
Min. Start Temp	-10 °C
Max. Operating Temp	
Warranty	5-year limited warranty
Labels	cETLus Damp location listed

P710051-009-30

Images:



Dimensions:

Width: 4-3/4"
Depth: 3"
Height: 16"
H/CTR: 12-5/8"

P710051-009-30**Dimming Notes:**

P710051 is designed to be compatible with many Triac/ELV controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

Lutron - NTELV-300

Lutron - DVELV-300P

Lutron - DVCL-253P

Lutron - Caseta Wireless

Leviton – 6672

Leviton – 6674

Leviton - 6681

Lutron - AYCL-153P

Lutron - TGCL-153PH

Lutron - AYLV-600P

Lutron - NTLV-600

Lutron - MAELV-601

Lutron - N-600

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.