







6 Volt and 12 Volt Heavy Duty emergency lighting unit has remote capability, and is efficient and easy to install It is completely self-contained and fully-automatic

- ▶ Hi Battery Capacity Emergency Lighting Units
- ▶ Allow for multiple additional remote lamp heads
- ▶ Compact, low profile design in neutral finish
- ▶ Push to test switch
- ▶ Side and top conduit KO's
- ▶ Automatic low voltage disconnect (LVD).
- ▶ Universal transformer for 120 or 277 VAC operation
- ▶ Standard with two fully adjustable, glare free lighting heads, Par 36 Lamps
- ► Charge rate/power on LED indicator light
- ▶ 6 or 12 Volt premium grade, pure lead, maintenance-free batteries
- ▶ Use only Incandescent Remote Heads
- ▶ 5 Year Warranty

50 Watt Units



100 Watt Units



Cat. No.	Watts Per Unit	Maximum Heads for 4 hrs Operation	Maximum Heads for 2 hrs Operation	Maximum Heads for 1.5 hrs Operation	Case Qty
6-Volt Units with Remote Capacity 7.2 Watt Wedge Base Lamps					
73166	50	2	4	5	2
73170	100	4	9	12	2
12-Volt Units with Remote Capacity 9 Watt Wedge Base Lamps					
73176	50	2	3	5	2
73180	100	4	7	10	2